Case A (106)

Casing for Ajax device

Compatibility	Superior LineSplit Fibra
Compatibility	Superior LineSplit Fibra
	Superior MultiRelay Fibra
Device installation	Number of devices
	To install more devices, select a model with a different number of slots: • Case B (175); • Case C (260); • Case D (430).
	Plastic latches
	to secure a device
	Slide the latches to remove the device.
	Cable fasteners
	to hold the cables together with ties
	Plastic stoppers
	to protect the installed device
	During drilling, the drill bit rests on the Case
	stoppers.
	Bubble level
	To check the inclination angle of the mount
	during installation.
	Recesses for drilling
	Ø16 mm or Ø20 mm
	The drill bit is fixed in the recess and does not
	move during drilling. We recommend using a hole saw for plastic.
	note saw for plastic.
	Wider holes
	To ensure that the casing is installed correctly,
	even if there are errors during installation.
Key features	Tamper board Included in the Case complete set. The tamper board connects to the appropriate device connector and protects the installed device from sabotage.
	Subotage.

	Rotate the device by 180° The device is fixed in two positions. You can turn it 180. Holding screws in the casing lid Rotate the lid by 180° The lid of Case A (106) can be rotated 180° during installation. Latches
	to secure the lid during installation The latches prevent the lid from falling off Case until it is secured with screws.
Recommendations	The device is designed for indoor use only. Case is produced in several versions.
Product	Dimensions 106 × 168 × 56 mm 4.17" × 6.61" × 2.20" Weight 186 g 6,56 oz Operating temperature range from -10 °C to +40 °C from 14 °F to 104 °F Operating humidity up to 75% Protection class IP20
Colours	Black White
Complete set	Case A (106) Tamper board Installation kit Quick start guide
Warranty	24 months