Case B (175)

Casing for Ajax devices

Compatibility	LineSplit Fibra Superior LineProtect Fibra
	Superior MultiRelay Fibra
Devices installation	Number of devices 2 To install a different number of devices, select a model with the appropriate number of slots: • Case A (106); • Case C (260); • Case D (430).
	Plastic latches to secure devices Slide the latches to remove the device.
	Cable fasteners to hold the cables together with ties
	Plastic stoppers to protect the installed devices During drilling, the instrument rests on the Case stoppers.
	Bubble level To check the inclination angle of the casing during installation.
	Recesses for drilling Ø16 mm or Ø20 mm The drill bit is fixed in the recess and does not move during drilling. We recommend using a hole saw for plastic.
	Wider holes To ensure that the casing is installed correctly, even if there are errors during installation.
Key features	Tamper board Included in the Case complete set. The tamper board connects to the appropriate connector of one of the devices and protects the installed devices from sabotage.

	Rotate devices by 180° The devices can be rotated by 180°, giving two options for fixation. Holding screws in the casing lid Rotate the lid by 180° The lid of Case B (175) can be rotated by 180° during installation. Latches to secure the lid during installation The latches prevent the lid from falling off Case until it is secured with screws.
Recommendations	The device is designed for indoor use only. Case is produced in several versions.
Product	Dimensions 175 × 225 × 57 mm 6.89" × 8.86" × 2.24" Weight 414 g 14.6 oz Operating temperature range from -10 °C to +40 °C from 14 °F to 104 °F Operating humidity up to 75% Protection class IP20
Colours	Black White
Complete set	Case B (175) Tamper board Installation kit Quick start guide
Warranty	24 months