


Superior Button Jeweller

Wireless panic button / smart button



What's new

BASELINE Button Jeweller	SUPERIOR Superior Button Jeweller
Available for all PROs	Available only for accredited partners

This is a device of the Superior product line. Only accredited Ajax Systems partners can sell, install, and administer Superior products.


Operating modes

Superior Button Jeweller supports 3 modes: **panic button**, **automation device control**, and **mute interconnected fire alarm**. Operating mode is adjusted by the PRO or user with admin rights in Ajax apps.

Event types


Superior Button Jeweller supports numerous event types, including **intrusion**, **fire**, **auxiliary alarm**, **panic button**, **gas alarm**, **malfunction**, **leakage**, and **custom**. Event type is adjusted by the PRO or user with admin rights in Ajax apps.

Protection against accidental alarm activation: double or long press




Jeweller communication technology

- Up to 1,300 m (4,250 ft) of radio communication in an open space
- Encryption and device authentication to prevent spoofing
- Regular polling to display the current device state



Flawless autonomy


- Up to 5 years of operation
- Pre-installed battery
- Low battery warning
- Battery state supervision



Quick installation and setup




- Pairing with a hub via QR code
- Remote control and configuration in Ajax apps
- Options to carry the device around on the wrist, on the neck, or on the key ring
- Fixing on a flat surface with the Holder bracket (sold separately)



<div>Compatibility with hubs and range extenders</div> <div></div> <div>For detailed information, scan the QR code or follow the link: ajax.systems/tools/devices-compatibility/?models=BT.S.J</div>	<div>Compliance with standards</div> <div>EN 50131-3 (Grade 2) INCERT SSF NFA2P</div>	<div>Communication with a hub or range extender</div> <div>Jeweller communication technology</div> <div>Frequency bands 868.0–868.6 MHz</div> <div>Communication range up to 1,300 m up to 4,250 ft In an open space</div>	<div>Power supply</div> <div>Battery 1 × CR2032 Pre-installed</div> <div>Battery life up to 5 years</div> <div>Manufacturer Renata</div>
<div>Installation</div> <div>Operating temperature range from –10°C to +40°C from 14 °F to 104 °F</div> <div>Operating humidity up to 75%</div> <div>Protection class IP55</div>	<div>Enclosure</div> <div>Color white, black</div> <div>Dimensions 47 × 35 × 13 mm 1.85" × 1.38" × 0.51"</div> <div>Weight 16 g 0.56 oz</div>	<div>Complete set</div> <div>Superior Button Jeweller 1 × CR2032 battery (pre-installed) Double sided tape Quick start guide</div>	



For detailed information, scan the QR code or follow the link:
ajax.systems/support/devices/superior-button-jeweller/

-  support@ajax.systems
-  @AjaxSystemsSupport_Bot
-  ajax.systems